



ALS 04

Alarm and monitoring center



An exceptional value for money (**quality / price ratio**) as effective monitoring of your livestock housing.

Because animal health is very sensitive to environmental conditions within the buildings, having an effective monitoring system for your farm buildings is vital. The ALS 04 brings an economic and efficient solution expected (**required**) by breeders.

☑ Effective monitoring and alarming

With its 4 monitoring loops, the ALS 04 detects all defaults, incidents or malfunctions as soon as they occur and quickly alerts the farmer by sound alarm (**siren**) or transmitter.

☑ Meeting (**compliance with**) standards

The ALS 04 complies with the main european standards and with agricultural insurance specifications.

☑ Quality / Price performance

The price of the ALS 04 is an economic success story, underlined by the reputed (**acknowledged**) quality and reliability of SODALEC's products.

The accessory BCL 08 : essential when you run several areas or buildings. The BCL 08 alarm loop report indicates in which room or building the default or problem is located. It manages up to eight rooms, areas or buildings, and can be cascaded to keep control on more of them.



BCL 08

- Polycarbonate waterproof box
- Single or 3 phases 230V Power supply for main monitoring.
- Battery Charger,
- Internal slot for a 12 V / 1,9Ah battery,
- Continuous monitoring of temperatures and general operations,
- Immediate indication of the fault with display of the concerned sensor on front panel,
- 4 monitoring loop inputs,
- Input for remote alarm timer,
- Siren/Alarm output 12 V DC - 1A,
- Transmitter output by voltage-free contact meeting French Standards (NF)
- Faulty battery output by voltage-free contact meeting French Standards (NF),
- Power Supply output 12V DC - 0,2A for transmitter,
- Periodic automatic battery check,
- Timed « alarm stop » button,
- Test button for outputs (siren and transmitter).

Fonctions overview



- ① Loops inputs French Standards (N.F)
- ② AC Power
- ③ Phase
- ④ Neutral
- ⑤ Ground
- ⑥ 12V Power Supply - Phone transmitter
- ⑦ Output - Phone transmitter
- ⑧ Output - Battery default
- ⑨ Output - Siren